



1.8 MHz through 30 MHz HF BPF set

- T2 4T #30 AWG bifilar on BN-43-2402 core
- T3 Primary 4T #30 AWG on BN-43-2402 core
- T3 Secondary 2T bifilar, #30 AWG over Primary

- L1/L3 45T #30 AWG, 18 inches, on T26-6 core
- L2 31T #30 AWG, 13 inches, on T25-6 core
- L4/L6 27T #30 AWG, 12 inches, on T25-6 core
- L5 13T #30 AWG, 7 inches, on T25-6 core
- L7/L9 19T #30 AWG, 9 inches, on T25-6 core
- L8 10T #30 AWG, 6 inches, on T25-6 core
- L10/L12 13T #30 AWG, 7 inches, on T25-6 core
- L11 7T #30 AWG, 5 inches, on T25-6 core

SoftRock Projects

RX Ensemble

Tony KB9YIG

5/30/10

Page 2 of 2